

# You are not working alone...

SOS Call



Fall Down Alert



Check in Alert







Real Time Location



Speaker Phone



GeoFencing

# S911 Lola S for Lone Workers

Law Enforcement, Security Guards, Drivers, Real Estate Agents, Postal Workers




## S911 Lola S for Lone Workers











The International Data Corporation (IDC) estimates that approximately 1.3 billion people are mobile-lone-workers. Many of these mobile workers work alone continuously throughout their workday. The lone workforce has brought new challenges for safety - how can we keep our employees safe if they are working alone? Using technology to track worker location and movement as ways to ensure lone workers never feel truly alone. Not only will lone workers feel more connected to their employers, but a direct connection might increase productivity and retention. S911 Lola S provides immediate emergency calls by pressing the SOS button and notifying the supervisors in real-time of the lone worker's location. Employers can track the work schedules and generate on-site reports with geofencing features. The man-down alert and regular check-in features can provide peace of mind for the safety of the lone workers. Contact us for a demo of the S911 Lola S.

### TECHNICAL SPECIFICATIONS

- 4G LTE with GNSS Reciever (AGPS)
- Tracking Sensitivity: -165dBm
- Acquisition Sensitivity: -146dBm
- Time to First Fix Cold start: <35 seconds
- Time to First Fix Hot start: 1 second
- Autonomous Position Error (CEP): 1.2 m
- LTE Bands: B2, B4, B5, B12, B13, B14 (North & South America version)
- LTE Bands: B1, B3, B7, B8, B20 (Europe & Rest of the world version)
- Receive calls with auto-answer, or silent calls without ring tones
- Alert for approaching 500, 1000 or 2000 meters of two devices for restraining orders
- Email alert and SMS for up to 4 responders
- Mobile App for Android and iOS smartphones
- Battery lasts > 16 hours with reporting every 5 minutes
- Battery lasts > 25 hours with reporting every 10 minutes
- Maximum operation temperature: 60 °C
- Minimum operation temperature: -20 °C

### **FEATURES OF S911 LOLAS**

- SOS button for emergency call
- Speaker & MIC for 2-way voice communication
- Real-time position report based on time interval and distance
- travelled
- Smart Log when out of cellphone coverage
- 20 Geofence setting with inclusion/exclusion alert
- Fall detection with accelerometer
- False alarm auto-filtering
- Regular Check-in alert
- Vibration alert
- Li-Ion Polymer Battery 900mA/h with battery status report
- Voice assistance with multi-language



S911 Lola S with safety breakaway neck strap

Locate your S911 Lola S in real time on LocationNow.com



### **ORDERING INFORMATION**

S911 Lola S - N (North & South America version) S911 Lola S - E (European & Rest of World version)

