

Your Best Partner on Campus



S911 Lola S for Students and Staff




S911 Lola S for Students and Staff











Protecting students and staff on and off the campus is the top priority of colleges and universities. Current campus safety measures are ineffective in preventing assaults. Relying on a cellphone to make an emergency call or text someone for help in an emergency might not work. The S911 Lola S provides immediate emergency calls by pressing the SOS button and notifying the responders in real-time of the student's location. No time is wasted in a distress situation. Laipac's S911 Lola devices have been used worldwide since 2012 in over 80 countries. These products have helped to save lives and prevented many tragedies from happening. Contact us for a demo of the S911 Lola S.

TECHNICAL SPECIFICATIONS

- 4G LTE with GNSS Reciever (AGPS)
- Tracking Sensitivity: -165dBm
- Acquisition Sensitivity: -146dBm
- Time to First Fix Cold start: <35 seconds
- Time to First Fix Hot start: 1 second
- Autonomous Position Error (CEP): 1.2 m
- LTE Bands: B2, B4, B5, B12, B13, B14 (North & South America version)
- LTE Bands: B1, B3, B7, B8, B20 (Europe & Rest of the world version)
- Receive calls with auto-answer, or silent calls without ring tones
- Alert for approaching 500, 1000 or 2000 meters of two devices for restraining orders
- Email alert and SMS for up to 4 responders
- Mobile App for Android and iOS smartphones
- Battery lasts > 16 hours with reporting every 5 minutes
- Battery lasts > 25 hours with reporting every 10 minutes
- Maximum operation temperature: 60 °C
- Minimum operation temperature: -20 °C

FEATURES OF S911 LOLA S

- SOS button for emergency call
- Speaker & MIC for 2-way voice communication
- Real-time position report based on time interval and distance travelled
- Smart Log when out of cellphone coverage
- 20 Geofence setting with inclusion/exclusion alert
- Fall detection with accelerometer
- False alarm auto-filtering
- Regular Check-in alert
- Vibration alert
- Li-Ion Polymer Battery 900mA/h with battery status report
- Voice assistance with multi-language



Locate your S911 Lola S in real time on LocationNow.com



ORDERING INFORMATION S911 Lola S - N (North & South America version) S911 Lola S - E (European & Rest of World version)

